

How to get pop-up window under event in HDMI2 Quick Guide

HIKVISION TECHNICAL SUPPORT TEAM

2021-08-20



How to get pop-up window under event in HDMI2

1

Preparation

Before you configure it, you need to connect screen1 as the operation screen, and connect the screen2 to HDMI2 output as pup-up motion screen. You need to configure in the local side.

Step 1: In local side, goes to the menu: Setting-live view-General:

- 1) Set the Video Output Interface as: HDMI1/VGA
- 2) Set the Event Output as: HDMI2
- 3) Then apply. See the picture below:

NV	/R 4.0		Se S	$\square $	۲.		0	Ŋ		± 4	<u>,</u> D	10
¢	General		Video Output Interface	HDMI1/VGA		Г	Event Output		HDMI2	1		
2	User		Live View Mode	3*3	-	L	Full Screen Monit	oring Dwell Time	10s			
	Network	>	Dwall Time	No Switch			, A	,				
	Event	>	Dweir nine	NO SWIGT								
	Live View	~	Enable Audio Output									
	General		Volume	1	5	3						
	View											
	Channel-Zero											
Ð	RS-232		Apply									
	Holiday											
	POS											
6	Audio Management											

Step 2: Goes to the menu: Live View-View:

- 1) Choose Video Output Interface HDMI1/VGA and set the cameras in different channels.
- 2) Choose Video Output Interface HDMI2 and set the camera you want to pup-up motion, save the menu: Start live view of all channels.
- 3) Then apply. See the picture below:

NV	'R 4.0								۲					
Ô	General		Video Output	Interface	HDMI2									
Ω	User					0		@ 2		© 3		A A		
	Network	>	Comora No.	L Cama	ca Mama	<u> </u>								
Ē	Event	>	D1	Came	ra				D2		D4		D6	
2	Live View	~	D2	Came	ra 01									
	General		D4	1124	01	5		8		⊗ 7		8 🛞		
	View		D6	Came	ra 01		D7		D8		D9		D10	
	Channel-Zero		D8	Came	ra 01									
Ξ	RS-232		D9	Came	ra 01	9		10 10		11 1		12		
	Holiday		D14	IPCan	nera 01									
	POS		D15	IPCan	nera 01		D14		D15		+			
	Audia Managamant													
2	Addio Management					13		14		15		16		
												Start live	view of all	
								⊞ ⊞				© 😰 🗘	P: 1/2	2 >

© Hikvision Digital Technology Co., Ltd. All Rights Reserved.



Step 3: Goes to menu: Setting-Event-Normal Event-Motion Detection:

- 1) Choose the camera you want and Enable it.
- 2) In Linkage Action, configure the Normal Linkage as Full Screen Monitoring and Apply.

General User Network Event	>	Motion Detection Video Camera [D1] C Enable Area Arming Schedu	Tampering Video Loss	Alarm Input Alarm C	Dutput Exception	
Normal Event Live View RS-232 Holiday POS Audio Management	>	Normal Linkage	Trigger Alarm Output Local->1 Local->2 Local->3 Local->4 Local->5 Clucal->2	Trigger Ch 2D1 D2 D4 D6 D7	Audio and Light Alar	
		*Notice: please confirm	the event output in "Live Vie	v [#] settings menu is the	e same with the real event output.	

Note:

If you configure the motion detection and alarm, then you will get pup-up motion screen in HDMI2.

First Choice for Security Professionals Hikvision Technical Support