

Title:	How to Set Pin Code Authentication on Access Control	Version:	v1.0	Date:	10/24/2018
	Device				
Product:	Access Control			Page:	1 of 4

## Preparation

- 1. This guide takes DS-K2604(firmware version: V2.0.4 build 180913) as an example to introduce how to set Pin code authentication on Access Control device.
- 2. Please download latest iVMS-4200 software and add device in advance.

## How to Set Pin Code Authentication on Access Control Device

## Steps:

1) Run iVMS-4200, click Modules Customization, add Access Control module.





Title:	How to Set Pin Code Authentication on Access Control	Version:	v1.0	Date:	10/24/2018
	Device				
Product:	Access Control			Page:	2 of 4

2) Go to Access Control>Advanced Function>Authentication Code, assign code to each card which is linked to access control device. Click Save.

File	System View	Tool Help		i۱ 📥	/MS-4200		admin 🏵 🕮 🛗 1	8:40:50 🔎	- • ×
==	Control Panel 🗛 Access Control 🖨 Device Management								
P	Access	🖪 Card Re 🛗 M	ulti 📼 Open 🛙	0	# Cross-Controller.	盾 Multi	IIII Authe 相 Ele	🗔 Cust.	. 🧏 Bla
66	Controller List		Card List				Authentication	n Password	🖬 Save
<b>B</b>	Search	9	_				Filter	2	
	. 10.9.98.	55	Card No.	Person Name	Password				
			0592486064	0592486064	123456				
V			0591960624	0591960624	654321	_			
-						3			
¢.	1								
<b>L</b>									
o									

3) Switch to **Card Reader Authentication page**, choose a card reader, Click **Configuration** to add Card or Authentication password mode to the Selected Mode list. Click Save.

File	System View Tool H	Help				VM:	S-4200			admin	<b>@</b>		8:45:29	e – –	×
	Control Panel	📕 Access C	Control	🚔 Dev	vice Man	ager	nent								
	Access 尾 Card	Re 聞 Mu	ulti 📼 (	Open D 耳	Anti	#	Cross-Contro	oller	🖻 Multi	. IIII Auth	ie 汩	Ele	🗔 Cu	st 🧏 Bla	a
66	Controller List		Property									ĺ	Copy to	Save Save	
e.	Search	9	Card Rea	ader Name:	Entra	nce	Card Reader	1							
	😑 🎩 10.9.98.55									_			🗹 C	onfiguration	1
	🔚 Entrance C		C	onfigure Ca	rd Read	er A	uthenticatio	n Wode			·			1	1
	Tait Card R	Selectable M	lode:				Selected Mod	de:			leek		C Delete	💼 Clear	
. *	Tentrance C	Card			_^		Card			$\uparrow \downarrow$			v Delete	Ulcar	
\$	Exit Card R	Card and Pa	assword		- 10	$\gg$	Card and Pa	ssword		$\uparrow \downarrow$		20	22	24	
	Entrance C	Card Or Aut	thenticati	on Password		«	Fingerprint			$\uparrow \downarrow$					
S	The Entrance C	Pingerprint	nd Finger	2 print			Card Or Aut	ngerprin	t ion Doce	v T ↓		20	22	24	
	👕 Exit Card R	Card Or Fin	dernrint	princ			Caru Or Aut	nenticat	ION Pass	wola 🗸					
Ð		curd of fill	gerprint									20		24	
								C	ĸ	Cancel		20	22	24	
o			ma			-									
			Fri	0 2	4	6	8 1	0 12	14	16	18	20	22	24	
				0 2	4	6	8 1/	1 12	14	16	19	20	22	24	
			Sat		- ï -	Ÿ		J 12	1 1	10	10	20	- 22	24	
			_	0 2	4	6	8 1	0 12	14	16	18	20	22	24	
			Sun												

© Hangzhou Hikvision Digital Technology Co.,Ltd. All Rights Reserved.

No.555 Qianmo Road, Binjiang District, Hangzhou 310052, China • Tel: +86-571-8807-5998 • Fax: +1 909-595-0788 E-Mail: <u>support@hikvision.com</u> • <u>www.hikvision.com</u>



Title:	How to Set Pin Code Authentication on Access Control Device	Version:	v1.0	Date:	10/24/2018
Product:	Access Control			Page:	3 of 4

4) Choose **Card or Authentication Password mode**, drag mouse to finish Card Reader Authentication Week Schedule Settings, Click **Copy to week** and **Save**.





Title:	How to Set Pin Code Authentication on Access Control	Version:	v1.0	Date:	10/24/2018
	Device				
Product:	Access Control			Page:	4 of 4

## First Choice for Security Professionals *HIKVISION* Technical Support