HIKVISION

Title:	DS-PWA How to Upgrade DS-PSG-WI Wireless Siren	Version:	v1.0	Date:	07/15/2020
	by RS232 Cable				
Product:	AX Series Wireless Security Control Panel				1 of 6

Preparation

- 1. Wireless Siren DS-PSG-WI
- 2. RS232 serial port cable
- 3. Software SecureCRT and TFTP (/20 Alarm/Hikvision/11 Installation&How to/Tool/)
- 4. Firmware APS_IndoorSiren433_CN_STD_V1.2.0_build200618 (433MHz) APS_IndoorSiren868_EN_STD_V1.2.0_build200618 (868MHz)

How to Upgrade DS-PSG-WI Wireless Siren by RS232 Cable

To support AX Hub Wireless Control Panel 1.0.6 function, DS-PSG-WI Wireless Siren support Buzzer and LED function. In this situation, Wireless Siren DS-PSG-WI need to be upgraded by RS232 cable.

1. Connect laptop USB port with Wireless Siren by RS232 serial cable.



© Hangzhou Hikvision Digital Technology Co.,Ltd. All Rights Reserved. No.555 Qianmo Road, Binjiang District, Hangzhou 310052, China • Tel: +86-571-8807-5998 • Fax: +1 909-595-0788 E-Mail: <u>support@hikvision.com</u> • <u>www.hikvision.com</u>



Title:	DS-PWA How to Upgrade DS-PSG-WI Wireless Siren by RS232 Cable	Version:	v1.0	Date:	07/15/2020
Product:	AX Series Wireless Security Control Panel				2 of 6



2. Check the COM port in computer's device management.





Title:	DS-PWA How to Upgrade DS-PSG-WI Wireless Siren	Version:	v1.0	Date:	07/15/2020
	by RS232 Cable				
Product:	AX Series Wireless Security Control Panel				3 of 6

3. Open SecureCRT and configure below parameters.

COM8 👻	Flow Control
115200 -	DTR/DSR
8 🔻	
None 👻	
1	
connect on startup	✓ Sa <u>v</u> e session
	115200 8 None 1

4. Press U within 5 seconds when you Power on the device. It will show Waiting for the file to be sent:





Title:	DS-PWA How to Upgrade DS-PSG-WI Wireless Siren Version: v1.0		v1.0	Date:	07/15/2020
	by RS232 Cable				
Product:	AX Series Wireless Security Control Panel				4 of 6

5. Choose "Send Yomdem" as shown in below image.



6. Choose Firmware and Add to transfer list, and Click OK to start transfer.

🔚 Select Files to Send using Ymodem					
查找范围([):	Wireless Indoor Siren	- 6 👂 📂 🖽	•		
名称	^	修改日期	类型		
🖉 Indoor_Wir	reless_Siren_APP	2020/6/18 14:39	BIN 文件		
<			>		
文件名(N):			Add		
文件类型(工):	All Files (*.*)		~		
Elles to send:		_			
C:\Users\ruanzais	heng\Desktop\SecureCRTPortable\Wireless	I <u>R</u> emove			
Upload files as	ASCII <u>O</u> K	Cancel			

© Hangzhou Hikvision Digital Technology Co.,Ltd. All Rights Reserved.

No.555 Qianmo Road, Binjiang District, Hangzhou 310052, China • Tel: +86-571-8807-5998 • Fax: +1 909-595-0788 E-Mail: <u>support@hikvision.com</u> • <u>www.hikvision.com</u>



Title:	DS-PWA How to Upgrade DS-PSG-WI Wireless Siren	Version:	v1.0	Date:	07/15/2020
Product:	AX Series Wireless Security Control Panel			Page:	5 of 6

7. It will upgrade automatically after transfer finished. When showing 100%, means upgrade finished.



8. Power off Wireless Siren, and then power on to check the version.

				^
=	VERSION:	DS-19102 868M APP_VER1.2.0	=	
=	Jun 18	202014:38:35	=	
1				×



Title:	-PWA How to Upgrade DS-PSG-WI Wireless Siren Version: v1.0		Date:	07/15/2020	
	by RS232 Cable				
Product:	AX Series Wireless Security Control Panel				6 of 6

First Choice for Security Professionals *HIKVISION* Technical Support